



# CUTE

## 4 Channel Power Controller

[www.innova.no](http://www.innova.no)

**The Innova 4 channel Power Controller board provides power switching to 4 separate power outputs.**

**Communication is by RS-232 or RS-485.**

The unit has 4 power outputs for switching 12 to 48VDC loads. Current consumption on each power output is measured and can thus be displayed on the host system. The power outputs are fitted with "electronic fuses" where the trip level is set by the user and fuses are re-set from the host system. The power outputs are also fitted with 2-pole relays for isolating the output in case of electrical leakage in the external circuit connected to the output.

### Key features

- 4 switchable power outputs with electronic fuses
- Load voltage range: 12 - 48VDC
- Fitted with 2-pole relays for isolating the output

Remote control is possible via RS-232 or multi drop RS-485 communication. The unit is configured to act as a slave unit controlled from a master system. Several units can be controlled over a single RS-485 network.

## PHYSICAL I/O CONFIGURATION

4 switchable power outputs with electronic fuses

## POWER, CURRENT AND TEMPERATURE

Power supply voltage:	12 VDC
Current consumption: (excluding external loads)	150 mA
Number of power outputs:	4
Load voltage range:	12 - 48 VDC
Load current quantification:	10 bit
Load current measurement range:	11 A
Maximum load fuse level:	6 A
Temperature range:	0 °C to 70 °C

## SIZE AND MOUNTING INTERFACE

Size ( L x W x H ): 160 x 100 x 12 mm

Mounting: Rail mounting on the short edges.  
Alternatively mounted by 4 holes for M3 bolts, 1 in each corner 5 mm from the edges.

## TERMINALS

Power and serial: Phoenix MC1, 5/8-ST-3, 81 connector

Power outputs: Phoenix MC1, 5/4-ST-3, 81 connector